



LEGEND

- CONDUCTORS CONNECTED
- |— CONDUCTORS NOT CONNECTED
- ← CONDUCTOR INDICATING LOAD DIRECTION
- CURRENT TRANSFORMER

Only qualified electrical personnel should install this equipment.

- Before performing installation or maintenance, disconnect all sources of electric power.
- Use appropriate personal protective equipment (PPE) and follow safe electrical work practices.

Find diagrams for more configurations at wattwatchers.com.au/support

- Installation Notes:**
- 1) Refer to Solar Inverter documentation to confirm specific DRMO connection terminals and technical requirements. DRMO maximum signal voltage and current must not exceed contactor ratings.
 - 2) Auditor is DIN-rail mounted and requires 35mm wide space.
 - 3) Current transformer installation –
For grid monitoring, K → L arrow is towards load.
For solar monitoring, K → L arrow is away from solar.
 - 4) Current transformers must be suitably secured in position.
 - 5) All wiring shall be tidy and secured in accordance with the wiring rules in your jurisdiction.
 - 6) An existing or new protective device can be used depending on the regulations in your jurisdiction.
 - 7) For more information, refer to the quick start guide and wattwatchers.com.au/support

Place current transformer connected to...	On cables connected to...
Terminals 1+ and 4+	A-Phase
Terminals 2+ and 5+	B-Phase
Terminals 3+ and 6+	C-Phase

Issue	Description	Drawn	Appd	Date
A	For Approval	KS	TM	10/20
B	Final	KS	TM	11/20
C				
D				
E				
F				
G				
H				



COPYRIGHT 2020 BY WATTWATCHERS
ALL RIGHTS RESERVED. NO PART OF THE CONTENTS OF THIS DRAWING MAY BE REPRODUCED OR TRANSMITTED IN ANY FORM BY PARTIES OTHER THAN THOSE EMPLOYED BY OR ENGAGED BY WATTWATCHERS AND ONLY IN DIRECT CONNECTION WITH THE PURPOSE FOR WHICH THIS DRAWING HAS BEEN PROVIDED WITHOUT THE WRITTEN PERMISSION OF WATTWATCHERS

Client Details

Drawn By
KS
Date
10/20
Approved By
TM
Date
10/20

Project Title
SOLAR REMOTE DISCONNECTION DIAGRAMS

Drawing Title
A6M+3SW MONITORING 3-PHASE MAINS + SOLAR WITH GENERIC DRMO CONTROL

Project Code
20181082
Status
FA
Revision
B
Drawing No.
WW018061
Scale
NTS